



Monitoring GPRS

Error numbers

4point light 10W

March 2014

1 Monitoring GPRS – Error numbers

Error number	Description
General errors:	
0	phone failure
1	No connection to phone
2	phone-adaptor link reserved
3	operation not allowed
4	operation not supported
5	PH-SIM PIN required
10	SIM not inserted
11	SIM PIN required
12	SIM PUK required
13	SIM failure
14	SIM busy
15	SIM wrong
16	incorrect password
17	SIM PIN2 required
18	SIM PUK2 required
20	memory full
21	invalid index
22	not found
23	memory failure
24	text string too long
25	invalid characters in text string
26	dial string too long
27	invalid characters in dial string
30	no network service
31	network time-out
32	network not allowed - emergency calls only
40	network personalization PIN required
41	network personalization PUK required
42	network subset personalization PIN required
43	network subset personalization PUK required
44	service provider personalization PIN required

Error number	Description
45	service provider personalization PUK required
46	corporate personalization PIN required
47	corporate personalization PUK required
General purpose error:	
100	unknown
GPRS related errors to a failure to perform an Attach:	
103	Illegal MS (#3)*
106	Illegal ME (#6)*
107	GPRS service not allowed (#7)*
111	PLMN not allowed (#11)*
112	Location area not allowed (#12)*
113	Roaming not allowed in this location area (#13)*
GPRS related errors to a failure to Activate a Context and others:	
132	service option not supported (#32)*
133	requested service option not subscribed (#33)*
134	service option temporarily out of order (#34)*
148	unspecified GPRS error
149	PDP authentication failure
150	invalid mobile class
Easy GPRS® related errors	
550	generic undocumented error
551	wrong state
552	wrong mode
553	context already activated
554	stack already active
555	activation failed
556	context not opened
557	cannot setup socket
558	cannot resolve DN
559	time-out in opening socket
560	cannot open socket
561	remote disconnected or time-out
562	connection failed
563	tx error
564	already listening

Error number	Description
FTP related errors	
600	generic undocumented error
601	wrong state
602	can not activate
603	can not resolve name
604	can not allocate control socket
605	can not connect control socket
606	bad or no response from server
607	not connected
608	already connected
609	context down
610	no photo available
611	can not send photo
612	resource used by other instance
Network survey errors:	
657	Network survey error (No Carrier)*
658	Network survey error (Busy)*
659	Network survey error (Wrong request)*
660	Network survey error (Aborted)*
Misc errors:	
9000	Time out on reading data from the modem
9001	Answer from modem von not OK
9002	FTP error no "CONNECT"
9003	FTP error no "NO CONNECT"
9004	Time out on sending data to the modem (XON/XOFF)